

m o o o i[®]



Perch Light Wall Recessed

What is more poetic and elegantly captivating than a bird perched on a branch, flirting, singing and celebrating life?

Designer	Umut Yamac
Year of design	2016
Material	Steel, Aluminium, PP
Additional	Solid State LED

Technical



Input Voltage: 180-240V ~ 50/60Hz

Power Consumption: Max 5W

Colour Temperature: 2700K

Light source: Solid State LED

CRI: 80

Lumen: Small bird approx 90lm; large bird approx 150lm

Dimmable: 0 - 10V - , 1 - 10V - , PWM dimming

Please make sure the right provision

Recommended dimmer 0-10V dimmable

For fluent dimming behaviour we advise a dimmer that is compatible with the following specs:


Transformer type: Electronic Low Voltage (ELV) 0-10V Dim

Load type: Capacitive load (C-Type)


Dimmer type: 0-10V dimmable

Please note the functioning of the dimmer and the power supply combination can never be predicted, it always needs to be tested in practice.

Colour



Brass



White

Packaging

Wall:

H 21 cm | 8,4"

W 34 cm | 13,6"

D 83 cm | 33,2"

Colli 1/1

With packaging:

6KG | 13 lb

Wall Recessed:

H 15 cm | 6"

W 40 cm | 16"

D 70 cm | 28"

Colli 1/1

With packaging:

6KG | 13 lb
